


# FIELD REPLACEABLE UNIT DOCUMENTATION

## Satellite™

### 2060CDS/2100Series

#### BATTERY PACK REMOVAL



- 1 Turn the computer upside down as shown
- 2 Slide the **battery release lever** in the direction of the arrow
- 3 Pull the **battery pack** slightly forward and lift it out

#### OPTIONAL PCMCIA CARD REMOVAL



- 1 Pull out the **eject button** of the PC card to be removed
- 2 Press the **eject button** and remove the PC card

#### KEYBOARD REMOVAL



- 1 Open the display panel
- 2 Remove the **Keyboard holder** at the base of the keyboard

#### KEYBOARD REMOVAL



- 3 Remove **one M2x4 brass screw** and lift out the **keyboard metal brace**

# TOSHIBA

Tough Enough for Today's World.

### 2060CDS/2100Series


#### KEYBOARD REMOVAL



M2.5x4 black screw

1. Lift out the **keyboard** and lay it on the palm rest cover. Be careful not to apply pressure on the **keyboard cable**.
2. Remove **one M2.5x6 black screw** and lift out the **keyboard top cover** between the speakers.
3. Disconnect the **keyboard cable** from **PJ11** on the system board and remove the **keyboard**.

#### EXPANSION MEMORY REMOVAL



Memory clips


1. Turn the computer upside down.
2. Remove **two M2x3 black screws** and remove the **memory cover**.
3. Push the **memory clips** outward and pull the **memory module** out of the connector on a 45 degree angle.

#### HDD REMOVAL



HDD slot cover

1. Turn the computer upside down.
2. Remove **one M2.5x6 black screw** securing **HDD slot cover** and pull out the cover.



HDD bracket handle

3. Remove **one M2.5x4 black screw** securing the **HDD**.
4. Grasp the **HDD bracket handle** and pull to disconnect the **HDD**.

# TOSHIBA

Tough Enough for Today's World.

# FIELD REPLACEABLE UNIT DOCUMENTATION

Satellite™

## 2060CDS/2100Series

### MODEM REMOVAL




Modem board

Modem cable M2x3 silver screws M2x5 brass screw

- 1 Remove **two M2x3 silver screws** and **one M2x5 brass screw** securing the modem board
- 2 Lift up the right side of the **modem board** and remove it from the system board
- 3 Disconnect the **modem cable** from PJ2 on the modem board


### TOP COVER REMOVAL



M2.5x20 black screws PJ4 LCD cable PJ11 Right/Left speaker cable PJ303 PJ300 M2.5x4 black screw Membrane switch cable PJ10

- 2 Turn the computer right side up and open the display panel
- 3 Remove **two M2.5x20 black screws** and **one M2.5x4 black screw** securing the top cover
- 4 Disconnect the following five cables:
  - LCD cable from PJ4
  - FL cable from PJ5
  - Membrane switch cable from PJ10
  - Left speaker cable from PJ303
  - Right speaker cable from PJ304

### TOP COVER REMOVAL



- 1 Turn the computer upside down and remove the following **thirteen screws**:
  - 4 M2.5x20 black screws
  - 3 M2.5x6 black screws (one from HDD slot cover)
  - 5 M2.5x4 black screws from battery slot and back of the computer
  - 1 M2x16 black screw




- 5 Lift up the **back and left side of the top cover** about 1 in to release the left latch on the front (as owl) and 2) Push the right (arrow3) to clear the **volume control** from the top cover
- 6 Rotate the **top cover and display assembly** forward to release the right latch

# TOSHIBA

Tough Enough for Today's World.

### 2060CDS/2100Series

#### HDD AND BATTERY BOARD REMOVAL




1. Disconnect the following cables from the HDD/battery board:  
 -HDD cable from PJ750  
 -Battery power line cable from PJ753  
 -Sensor cable from PJ754
2. Remove one M2.5x6 brass screw
3. Lift up the HDD/battery board

#### CD ROM DRIVE REMOVAL




1. Disconnect the CD-ROM flexible cable from PJ301 on the system board
2. Remove one M2.5x4 brass screw securing the CD-ROM drive
3. Slide out the CD-ROM drive

#### FDD REMOVAL



1. Disconnect the FDD flexible cable from PJ15 on the system board
2. Remove one M2.5x4 brass screw and one M2.5x5 hex stud securing the FDD and lift the FDD out
3. Remove four M2.5x3 brass screws securing the FDD to the FDD case
4. Disconnect the FDD flexible cable from the FDD



4. Remove two M2x6 brass screws securing the CD-ROM connector assembly
5. Separate the CD-ROM connector and the connector brace from the CD-ROM drive
6. Disconnect the CD-ROM flexible cable from PJ760 on the CD-ROM connector
7. Remove two M2x3 screws securing the side brace

# TOSHIBA

Tough Enough for Today's World.

### 2060CDS/2100Series

#### RTC AND BACKUP BATTERY REMOVAL



RTC battery  
PJ700  
PJ701  
RTC battery cable

- 1 Open the RTC battery cover
- 2 Disconnect the RTC battery cable from PJ702 on the sound board
- 3 Lift out the RTC battery

#### SENSOR AND SOUND BOARD REMOVAL



Sound cable  
PJ700  
Sound board

- 1 Disconnect the sound cable from PJ700 on the sound board
- 2 Remove one M2.5x4 brass screw securing the sound board
- 3 Lift up the sound board

#### SYSTEM BOARD REMOVAL

M2.5x4 brass screws M2.5x6 brass screw



M2.5x4 brass screws  
Heat sink duct  
Heat sink holder  
Insulator  
M2.5x4 flat head screws  
PJ700

- 1 Remove plastic stud and insulator
- 2 Disconnect the sound cable from PJ700 on the sound board
- 3 Remove the following seven screws securing the heat sink, system board and PC card slot cover:
  - 2 M2.5x4 flat head brass screws
  - 3 M2.5x4 brass screws
  - 3 M2.5x6 brass screw
- 4 Lift out the heat sink duct and remove the heat sink by unlatching the heat sink holder from the tab of the CPU socket

PC card slot cover System board Battery power cable



Sound cable  
HDD/battery cable

- 5 Lift out the system board from the front end and remove the PC card slot cover
- 6 Disconnect the following cables from the system board:
  - HDD/battery cable from PJ300
  - Battery power cable from PJ501
  - Sound cable from PJ302

# TOSHIBA

Tough Enough for Today's World.

### 2060CDS/2100Series


#### MEMBRANE SWITCH REMOVAL



M2x4 brass  
screws  
Membrane  
switch

- 1 Remove **two M2x4 brass screws** securing the membrane switch
- 2 Lift up the **membrane switch**

#### SPEAKERS REMOVAL




Tape  
Speakers

M2x4 flat head screws

- 1 Remove **two M2x4 flat head screws** securing each speaker
- 2 Remove the **tape** securing the speaker cables and lift out the **speakers**

#### COOLING FAN REMOVAL



M2x4 flat head  
silver screws  
Tape  
Fan cable  
PJ1

Cooling fan

- 1 Remove the **tape** covering **PJ1** and the fan cable
- 2 Disconnect the **fan cable** from **PJ1** on the system board
- 3 Remove **two M2.4 silver screws** securing the cooling fan
- 4 Take out the **cooling fan** from the system board


# TOSHIBA

Tough Enough for Today's World.

## Satellite™


## 2060CDS/2100Series

## DISPLAY MASK



- 1 Remove **two mask seals** at the bottom corners of the display assembly
- 2 Remove **two M2.5x6 brass screws**
- 3 There are **22 latches** securing the **display mask**. Carefully insert your fingers between the **display mask** and the **LCD module** and pry open the latches starting from the **top six latches** to the **five latches on the right** and **left sides**, ending with the **six bottom latches**

## FL INVERTER AND SCREEN REMOVAL



- 1 Remove **two M2.5x6 brass screws** securing **FL inverter board**
- 2 Carefully rotate the **FL inverter board** out from right to left then disconnect the **FL inverter cable** from **CN1** and the **HV cable** from **CN2**
- 3 Remove **four M2.5x6 brass screws** securing the **LCD module**
- 4 Carefully rotate the **LCD module** from right to left of the **LCD cover**
- 5 Disconnect the **LCD cable** from the **LCD module** and remove the **LCD** from the computer

TOSHIBA

Tough Enough for Today's World.